

**Cash Drawers Comparative Specifications**

CASH DRAWER GROUPS define the structure of the suspension & drawer release systems.	Groups								
	Moderate		Standard					Enhanced	
Moderate Electronic Cash Drawers have heavy-duty suspensions w/ steel ball-bearing nylon wheels installed on ABS drawers & steel drawer rail frames. Heavy-duty drawer release assy have operation solenoids. Series 40 has drawer status sensor.	x	x							
Standard Electronic Cash Drawers have heavy-duty suspensions w/ steel ball-bearing nylon wheels installed on steel drawers & frames & roll in steel channels. Drawer release assy have operation solenoids & drawer status sensors.			x	x	x	x	x		
Standard Manual Cash Drawer has heavy-duty suspension w/ steel ball-bearing nylon wheels installed on steel drawer & frame & roll in steel channels.					x				
Enhanced Electronic Cash Drawers have heavy-duty suspensions w/ steel ball-bearings steel slides installed on steel drawers & frames & roll in steel channels. Drawer release assy have operation solenoids & drawer status sensors.								x	x
<b>Housing</b>	<b>Housing</b>								
Black steel housing with molded ABS drawer does not accommodate a removable cash tray.	x	x							
Black steel housing with open steel drawer accommodates a removable cash tray.			x	x	x	x	x	x	x
Steel housings are reinforced which allows POS terminals, peripherals, etc to be placed on top.			x	x	x	x	x	x	x
Dual cable & cord drop-thru slots in back of cash drawer top & bottom.							x		
<b>Drawer</b>	<b>Drawer</b>								
Full extension drawer.	x	x	x	x	x	x	x	x	x
Emergency drawer release lever in housing bottom.		x	x	x		x	x	x	x
(2) position drawer security lock: locked open; locked closed (for manual cash drawer only).					x				
(3) position drawer security lock: locked open; locked closed; manual open.	x	x	x	x		x	x	x	x
Steel drawer front with (1) doc insert slots.								x	
Steel drawer front with (2) doc insert slots.			x	x	x	x	x		
ABS drawer front without any doc insert slot.	x								
ABS drawer front with (1) doc insert slot.		x				x			x
Multiple compartments/bins molded in deep bottom receive inserted docs & store of bill & coin wraps, etc.									x
<b>CASH DRAWER SERIES define the size, weight &amp; media storage configurations.</b>	<b>Series</b>								
	<b>20</b>	<b>40</b>	<b>200</b>	<b>300</b>	<b>400</b>	<b>500</b>	<b>600</b>	<b>1400</b>	<b>2400</b>
<b>Size</b> width x length x height given in whole inches & next fraction. ¼", ½", ¾".	13¼ 14½ 3¼	16¼ 16 4	13¼ 13½ 3¼	14¼ 15½ 3½	16¼ 16½ 4½	16¾ 18½ 4½	18¼ 18½ 4½	16¼ 16½ 4½	16 17 5¼
<b>Weight</b> rounded up to next whole pound.	8	12	10	12	16	18	19	19	23
<b>Media Storage</b> - Cash Drawers, Cash Trays & Coin Tills - Bill & Coin Compartments	<b>Media Storage</b>								
4B5C-Cash drawer has 4-bill compartments & a removable coin till with 5-compartments.	x								
5B5C-Cash drawer has 5-bill compartments & 5-coin compartments (removable coin till with 3-adjustable compartments).		x							
4B5C-Removable cash tray has 4-bill compartments & a removable coin till with 5-compartments.			x						
4B8C-Removable cash tray has 4-bill compartments & a removable coin till with 5-compartments.				x					
5B5C-Removable cash tray has 5-bill compartments & a removable coin till with 5-compartments.					x	x	x	x	
5B5C-Removable cash tray has 5-bill compartments & 5-compartments.									x
<b>CASH DRAWER MODELS define the system application by the last digit in the Model Number.</b>	<b>Models</b>								
<b>Model 1</b> - Manual Push Button Cash Drawer has heavy-duty push button drawer release assembly.					<b>401</b>				
<b>Model 2</b> - Electronic RJ 24V Cash Drawers work with Epson & Epson compatible POS receipt printers including JAY, Star, Citizen, etc. Printers emulate ESC/POS command support, have a 6P6CRJ12(F) drawer kick-out jack & output 24V to activate the cash drawer 24V drawer release system. The detachable interface cable has 6P6CRJ12(M) connector plugs.	<b>22</b>	<b>42</b>	<b>202</b>	<b>302</b>	<b>402</b>	<b>502</b>	<b>602</b>	<b>1402</b>	<b>2402</b>
<b>Model 5</b> - Electronic RJ12V Cash Drawers are the same as the RJ24V cash drawers except that they work with POS receipt printers that output 12V to activate the 12V drawer release system.	<b>25</b>	<b>45</b>	<b>205</b>	<b>305</b>	<b>405</b>	<b>505</b>	<b>605</b>	<b>1405</b>	<b>2405</b>
<b>Model 7</b> - Electronic RJ/DIN 12V Cash Drawers work with Micros POS Terminals that have 4PinDIN(F) drawer kick-out connector jacks & output 12V. Interface Cable has 6P6CRJ12(M) / 4PinDIN(M) plugs. Drawer status sensor is wired to Micros specifications to detect open/closed condition & control operation.		<b>47</b>	<b>207</b>	<b>307</b>	<b>407</b>	<b>507</b>	<b>607</b>	<b>1407</b>	<b>2407</b>
<b>Model 9</b> - Electronic USB 12V & 24V Cash Drawers work with POS terminals, PCs, etc. The user designated USB I/O outputs 5V to the JAY USB Interface Module which electronically steps it up to 12V or 24V to activate the 12V or 24V drawer release system. 6P6CRJ12(M) interface cable connects the drawer at the USB Module RJ(F) jack. USB(F) interface cable connects the terminal to the USB Module at the USB(F) jack. JAY USB Driver Software v2.6.1 & v3.0 are developed & supported by the Company. They act as if connected to a serial COM port. Software supports Microsoft Windows Operating Systems: XP - 32bit SP3 (MS support thru 4/14/14); Vista - 32/64bit SP2; 7 - 32/64bit SP1; 8 - 32/64bit; 8.1 - 32/64bit.	<b>29</b>	<b>49</b>	<b>209</b>	<b>309</b>	<b>409</b>	<b>509</b>	<b>609</b>	<b>1409</b>	<b>2409</b>
<b>Options</b>	<b>Options</b>								
Under counter mounting brackets.	x	x	x	x	x	x	x	x	x
Cash drawer substitute security lock random #0002~0199.					x	x	x	x	x
Cash tray locking lids.			x	x	x			x	x
Cash tray locking lid substitute lock random #002~199.			x	x	x	x	x	x	x
<b>In Box with Cash Drawer</b> - numbers refer to the system application last digit in the Model Number	<b>In the Box</b>								
Drawer Lock Keys (2).	x	x	x	x	x	x	x	x	x
Interface cable with 6P6CRJ12(M) plugs.	2,5,9	2,5,9	2,5,9	2,5,9	2,5,9	2,5,9	2,5,9	2,5,9	2,5,9
Interface cable with 6P6CRJ12(M) / 4PinDIN(M) plugs.		7	7	7	7	7	7	7	7
Interface cable with USB/(M)B plugs.	9	9	9	9	9	9	9	9	9
USB Interface Module.	9	9	9	9	9	9	9	9	9
<b>Lifetime Warranty</b> extends to JAY Brand Products used under normal operating conditions for the purpose intended.	x	x	x	x	x	x	x	x	x

**Click on Cash Drawer Model Number to open individual printer web page for pricing, ordering, etc.**